

Multi-Position Meter Mains

125/200 Amps | 22K AIC Rated | 240 VAC



U5882-X



U5906-X

Specifications

- 4 terminals with 5th terminal option.
- Horn bypass option available.
- Available in 60, 100, 150 & 200 amps.
- Optional barrel lock provision.
- Separate lockable breaker reset cover.
- Listed under UL 67 as "suitable only for use as service equipment"—file number E32628.
- 125 amps or 200 amps (per position) continuous duty ringless meter socket. Overall ampere rating limited to main circuit breaker rating.
- For use on 120/240 volt single phase applications.
- Short circuit withstand rating 22K AIC as standard. See wiring diagrams on back page for series rating compatibility.
- Type 3R enclosure constructed with G90 galvanized steel.
- Light gray polyester powder coat finish.
- Service entrance overhead or underground. OH has up to 4" hub opening and UG has up to 4" knockout.
- Wire terminations accept copper or aluminum conductors. Line & neutral: studs Ground: #14-2/0
- Plug-on main circuit breaker: 60 and 100 amp type **Q** small frame, 150 & 200 amp type **QNR** large frame.
- Lockable breaker reset cover.

4 Terminals | Multi-Position Meter Main | Ringless

| 125 Amps/Position Catalog Number | 200 Amps/Position Catalog Number | Positions | Service | Connectors CU/AL | Dimensions | | |
|-------------------------------------|-------------------------------------|-----------|---------|------------------|------------|----------|-----|
| | | | | Line | D" | W" | H" |
| U5902-X | U5882-X | 2 | OH/UG | 3/8" x 16 Stud | 5 1/8" | 26 1/2" | 30" |
| U5903-X | U5882-X | 3 | OH/UG | 3/8" x 16 Stud | 5 1/8" | 34 5/8" | 30" |
| U5904-X | U5882-X | 4 | OH/UG | 3/8" x 16 Stud | 5 1/8" | 42 1/2" | 30" |
| U5905-X | U5882-X | 5 | OH/UG | 3/8" x 16 Stud | 5 1/8" | 51 1/20" | 30" |
| U5906-X | U5882-X | 6 | OH/UG | 3/8" x 16 Stud | 5 1/8" | 59 3/10" | 30" |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.



Multi-Position Meter Mains

125/200 Amps | 22K AIC Rated | 240 VAC

Notes

- **Optional:** Factory installed breakers are available—consult factory.
- **AIC Rating:** All models are rated **22K AIC** when used with approved breakers rated at 22K.
- **Hub:** Units supplied with one (1) closing plate. Order hubs separately, see accessories page.
- **Fifth Terminal:** For field installed fifth terminal, order **K5T**.
- **Connectors:** Socket is supplied with 3/8" - 16 hex head nuts with Belleville washers. For connector lug kits, order as extra from chart on the accessories page. Separate lug kits are required for line and load.

Breaker Chart - 10K AIC (unless noted 22K)

| Manufacturer | Cutler Hammer | Siemens | G.E. (50 Amp Max) | Square D |
|------------------|---------------|---------------|-------------------|----------|
| 125 Amps or Less | BR, HQP, QPGF | QP, QPH (22K) | THQL, THQL-GF | Homeline |
| 150-200 Amp | — | QN, QNH (22K) | — | — |

Accessories

| | | | | | |
|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|
|  |  |  |  |  |  |
| K5T Fifth terminal | 112993 Meter front | 1135467 Lower front | 1133923 Wireway front | QN2200H Circuit breaker | Q2100H Circuit breaker |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.

