



# Current Transformer Cabinets

Northern Indiana Public Service Area Units | UL Listed

## Overhead Entry and Underground Exit

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-413       | 400  | 250     | 1Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-719   |
| NIPM-433       | 400  | 250     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-720   |
| NIPM-434       | 400  | 250     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-719   |
| NIPM-813       | 800  | 250     | 1Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-823A  |
| NIPM-833       | 800  | 250     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-888A  |
| NIPM-834       | 800  | 250     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-823A  |
| NIPM-1213      | 1200 | 250     | 1Ø3W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-898A  |
| NIPM-1233      | 1200 | 250     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-899   |
| NIPM-1234      | 1200 | 250     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-898A  |
| NIPM-1613      | 1600 | 250     | 1Ø3W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-857B  |
| NIPM-1633      | 1600 | 250     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-739   |
| NIPM-1634      | 1600 | 250     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-857B  |
| NIPM-2013      | 2000 | 250     | 1Ø3W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-737   |
| NIPM-2033      | 2000 | 250     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-738   |
| NIPM-2034      | 2000 | 250     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-22V       | 20104-737   |

## 600 VAC | 3Ø-4W | Units with Sidecar for Mounting 3 Voltage Transformers

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-464       | 400  | 600     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-719   |
| NIPM-864       | 800  | 600     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-823A  |
| NIPM-1264      | 1200 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-24V       | 20104-898A  |
| NIPM-1664      | 1600 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-24V       | 20104-857B  |
| NIPM-2064      | 2000 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-24V       | 20104-737   |

## 600 VAC | 3Ø-3W | Units with Sidecar for Mounting 2 Voltage Transformers

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-463       | 400  | 600     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-720   |
| NIPM-863       | 800  | 600     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-888A  |
| NIPM-1263      | 1200 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-24V       | 20104-899   |
| NIPM-1663      | 1600 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-24V       | 20104-739   |
| NIPM-2063      | 2000 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-24V       | 20104-738   |

## Notes

- All cabinets are hinged on the right (looking from the front of the cabinet).

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.





# Current Transformer Cabinets

Northern Indiana Public Service Area Units | UL Listed

## Underground Entry and Underground Exit

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-413       | 400  | 250     | 1Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-719   |
| NIPM-433       | 400  | 250     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-720   |
| NIPM-434       | 400  | 250     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-719   |
| NIPM-813       | 800  | 250     | 1Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-823A  |
| NIPM-833       | 800  | 250     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-888A  |
| NIPM-834       | 800  | 250     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-823A  |
| NIPM-1213UGBX  | 1200 | 600     | 1Ø3W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-898A  |
| NIPM-1233UGBX  | 1200 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-899   |
| NIPM-1234UGBX  | 1200 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-898A  |
| NIPM-1613UGBX  | 1600 | 600     | 1Ø3W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-857B  |
| NIPM-1633UGBX  | 1600 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-739   |
| NIPM-1634UGBX  | 1600 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-857B  |
| NIPM-2013UGBX  | 2000 | 600     | 1Ø3W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-737   |
| NIPM-2033UGBX  | 2000 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-738   |
| NIPM-2034UGBX  | 2000 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-25V       | 20104-737   |

## 600 VAC | 3Ø-4W | Units with Sidecar for Mounting 3 Potential Transformers

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-464       | 400  | 600     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-719   |
| NIPM-864       | 800  | 600     | 3Ø4W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-823A  |
| NIPM-1264UGBX  | 1200 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-26V       | 20104-898A  |
| NIPM-1664UGBX  | 1600 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-26V       | 20104-857B  |
| NIPM-2064UGBX  | 2000 | 600     | 3Ø4W  | 85kA | 60         | 38 | 16 | 20104-26V       | 20104-737   |

## 600 VAC | 3Ø-3W | Units with Sidecar for Mounting 2 Potential Transformers

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-463       | 400  | 600     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-720   |
| NIPM-863       | 800  | 600     | 3Ø3W  | 65kA | 48         | 25 | 10 | 20104-23V       | 20104-888A  |
| NIPM-1263UGBX  | 1200 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-26V       | 20104-899   |
| NIPM-1663UGBX  | 1600 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-26V       | 20104-739   |
| NIPM-2063UGBX  | 2000 | 600     | 3Ø3W  | 85kA | 60         | 38 | 16 | 20104-26V       | 20104-738   |

## Notes

- All cabinets are hinged on the right (looking from the front of the cabinet).
- All cabinets ending in "UGBX" have a side gutter installed on the left side of the cabinet.

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.





# Current Transformer Cabinets

Northern Indiana Public Service Area Units | UL Listed

400 Amps | 1Ø-3W, 600 VAC | Cabinets That Use Double Bar CT, JCA-0C  
Overhead Entry and Underground Exit | Underground Entry and Underground Exit

| Catalog Number | Amps | Voltage | Phase | SCCR | Dimensions |    |    | Cabinet Drawing | Bus Drawing |
|----------------|------|---------|-------|------|------------|----|----|-----------------|-------------|
|                |      |         |       |      | H"         | W" | D" |                 |             |
| NIPM-463DBCT   | 400  | 600     | 1Ø3W  | 65kA | 48         | 25 | 10 | 20104-21V       | 20104-820   |

## Notes

- All cabinets are hinged on the right (looking from the front of the cabinet).

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.

