

## UAP9801-RRL



| Catalog Number                | UAP9801-RRL   |
|-------------------------------|---|
| Marketing Product Description | 4 Terminal Ringless Large Hub<br>Open Adapt To Small Hub<br>Open Lever Bypass Aluminum<br>Painted |
| UPC                           | 784572286528  |
| Length (IN)                   | 4.844   |
| Width (IN)                    | 13  |
| Height (IN)                   | 19  |
| Brand Name                    | Milbank   |
| Туре                          | Ringless Meter Socket   |
| Application                   | Meter Socket  |
| Standard                      | UL Listed;Type 3R   |
| Voltage Rating                | 600 Volts Alternating Current   |
| Amperage Rating               | 200 Continuous Ampere   |
| Phase                         | 1 Phase   |
| Frequency Rating              | 60 Hertz  |
| Size                          | 4.844L x 13W x 19H  |
| Number Of Cutouts             | 0   |
| Cutout Size                   | No Main Breaker   |
| Cable Entry                   | Overhead or Underground   |
| Terminal                      | Lay in  |
| Insulation                    | Glass Polyester   |
| Mounting                      | Surface Mount   |
|                               |   |

| Enclosure                 | Aluminum with Powder Coat<br>Finish            |
|---------------------------|--|
| Jaw Quantity              | 4 Terminal                                     |
| Bypass Type               | Lever Bypass                                   |
| Number of Meter Positions | 1 Position                                     |
| Equipment Ground          | Bonded Ground Strap                            |
| Hub Opening               | Large Hub Opening Adapted to Small Hub Opening |
| Line Side Wire Range      | 6 AWG - 350 kcmil                              |
| Load Side Wire Range      | 6 AWG - 350 kcmil                              |
| Number Of Receptacles     | 0  |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.