## MILBANK ENERGYAT WORK

## U5842-RL-100-KK



| Catalog Number                | U5842-RL-100-KK  |
|-------------------------------|--|
| Marketing Product Description | 4 Terminal Ringless Small Hub<br>Open 1-100 Ampere Main<br>Breaker Horn Bypass |
| UPC                           | 784572512542   |
| Length (IN)                   | 4.125  |
| Width (IN)                    | 8  |
| Height (IN)                   | 30   |
| Brand Name                    | Milbank  |
| Туре                          | Ringless Meter Socket  |
| Application                   | Meter Socket With Main   |
| Standard                      | UL Listed;Type 3R  |
| Voltage Rating                | Up to 240 Volts Alternating<br>Current   |
| Amperage Rating               | 200 Continuous Ampere  |
| Phase                         | 1 Phase  |
| Frequency Rating              | 60 Hertz   |
| Size                          | 4.125L x 8W x 30H  |
| Number Of Cutouts             | 1  |
| Cutout Size                   | One 100 Ampere Main<br>Breaker   |
| Cable Entry                   | Overhead   |
| Terminal                      | Lay in   |
| Insulation                    | Glass Polyester  |

| Mounting                  | Surface Mount                                   |
|---------------------------|---|
| Enclosure                 | G90 Galvanized Steel with<br>Powder Coat Finish |
| Jaw Quantity              | 4 Terminal                                      |
| Bypass Type               | Horn Bypass                                     |
| Number of Meter Positions | 1 Position                                      |
| Equipment Ground          | 2 Barrel Ground Lug                             |
| Hub Opening               | Small Hub Opening                               |
| Line Side Wire Range      | 6 AWG - 350 kcmil                               |
| Load Side Wire Range      | 4 - 1/0 AWG                                     |
| Number Of Receptacles     | 0   |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.