## MILBANK ENERGYAT WORK

## U2864-X



Catalog NumberU2864-XMarketing Product DescriptionA Terminal Ringless Large Closing Plate 4 Position 4-200 Ampere Main Breaker Provision Double Connector 4-600kcmilUPC784572136335Length (IN)4.844Width (IN)36Height (IN)29Brand NameMilbankTypeRingless Meter SocketApplicationUL Listed;Type 3RStandardUL Listed;Type 3RVoltage Rating200 Continuous Ampere
Closing Plate 4 Position 4-200 Ampere Main Breaker Provision Double Connector 4-600kcmilUPC784572136335Length (IN)4.844Width (IN)36Height (IN)29Brand NameMilbankTypeRingless Meter SocketApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
Length (IN)4.844Width (IN)36Height (IN)29Brand NameMilbankTypeRingless Meter SocketApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
Width (IN)36Height (IN)29Brand NameMilbankTypeRingless Meter SocketApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
Height (IN)29Brand NameMilbankTypeRingless Meter SocketApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
Brand NameMilbankTypeRingless Meter SocketApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
TypeRingless Meter SocketApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
ApplicationMeter Socket With MainStandardUL Listed;Type 3RVoltage RatingUp to 240 Volts Alternating Current
StandardUL Listed; Type 3RVoltage RatingUp to 240 Volts Alternating Current
Voltage Rating Up to 240 Volts Alternating   Current
Current
Amperage Rating     200 Continuous Ampere
Phase 1 Phase
Frequency Rating 60 Hertz
Size 4.844L x 36W x 29H
Number Of Cutouts 0
Cutout Size Breaker Provision
Cable Entry Overhead or Underground
Terminal 3/8 Inch Stud

Mounting	Surface Mount
Enclosure	G90 Galvanized Steel with Powder Coat Finish
Jaw Quantity	4 Terminal
Bypass Type	No Bypass
Number of Meter Positions	4 Positions
Equipment Ground	Ground Lug
Hub Opening	Large Closing Plate
Number Branch Circuits	4
Number Of Receptacles	0

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.