



**MILBANK**  
ENERGY AT WORK

## Z708767-MO



|                               |                                   |
|-------------------------------|-----------------------------------|
| Catalog Number                | Z708767-MO                        |
| Marketing Product Description | Receptacle 50 Ampere              |
| UPC                           | 784572570832                      |
| Length (IN)                   | 2.173                             |
| Width (IN)                    | 2.25                              |
| Height (IN)                   | 3.71                              |
| Weight (LB)                   | 0.35                              |
| Brand Name                    | Milbank                           |
| Type                          | Metering Accessory                |
| Application                   | Power Outlet                      |
| Standard                      | UL Listed                         |
| Number Of Poles               | 2                                 |
| Number Of Wires               | 4 Wire                            |
| Wire Size                     | 8 AWG                             |
| Amperage Rating               | 50 Ampere                         |
| Voltage Rating                | 120/240 Volts Alternating Current |
| Wattage                       | 12,000 VA Maximum                 |
| Phase                         | 1 Phase                           |
| Material                      | Thermoplastic                     |
| Color                         | Black                             |
| NEMA Rating                   | NEMA 14-50                        |
| Mounting                      | Enclosure                         |

|                    |                         |
|--------------------|-------------------------|
| Connection         | Terminals               |
| Size               | 2.173L x 2.25W x 3.710H |
| Temperature Rating | No Temperature Rating   |

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.